

Halogen Lamps PIR Sensor, Model : HC-150W / HC-500W



The infrared induced lamp has an infrared detector within it. When the thermal body moving in the darkness the detector will light the lamp automatically and turn off after a period of time set in advance.

MODEL : HC 150W (150 WATTS HALOGEN LAMP)

MODEL : HC 500W (500 WATTS HALOGEN LAMP)

Features

1. PIR Motion Sensor with Floodlight
2. Sensitivity control Option
3. LUX & Time adjustment

Specification

Detection Angle	: 180°
Power Source	: 110-130V/AC 220-240V/AC
Power Frequency	: 50/60Hz
Rated Load	: Max. 1200W (220-240V/AC)
Detection Distance	: 5-12m (<24°C) adjustable
Time Delay	: 10sec±3sec to 7min±2min(adjutable)
Ambient Light	: < 3-2000LUX(adjutable)
Detection Motion Speed	: 0.6-1.5m/s

Detection Pattern



Applications

1. Covered / Semi Covered Parking Area
2. Backyard / Garden Area
3. Balcony / Stairways
4. Terrace / Basements